

g -ELEMENTS OF MATROID COMPLEXES

EDWARD SWARTZ

ABSTRACT. A g -element for a graded R -module is a one-form with properties similar to a Lefschetz class in the cohomology ring of a compact complex projective manifold, except that the induced multiplication maps are injections instead of bijections. We show that if $k(\Delta)$ is the face ring of the independence complex of a matroid and the characteristic of k is zero, then there is a non-empty Zariski open subset of pairs (Θ, ω) such that Θ is a linear set of parameters for $k(\Delta)$ and ω is a g -element for $k(\Delta)/\langle \Theta \rangle$. This leads to an inequality on the first half of the h -vector of the complex similar to the g -theorem for simplicial polytopes.

1. INTRODUCTION

The combinatorics of the independence complex of a matroid can be approached from several different directions. The f -vector directly encodes the number of independent sets of every cardinality, while the h -vector contains the same information encoded in a way which is more appropriate for reliability problems [4]. In either case the fundamental question is the same. What vectors are possible?

Let $(h_0, h_1, \dots, h_r)$ be the h -vector of the independence complex of a rank r matroid without coloops. Using a PS-ear decomposition of the complex Chari [6] proved that for all $i \leq r/2$, $h_i \leq h_{r-i}$ and $h_{i-1} \leq h_i$. By showing that the h -vector was the Hilbert function of $k(\Delta)/\langle \Theta \rangle$, where $k(\Delta)$ is the face ring of the complex and Θ is a linear system of parameters for $k(\Delta)$, Stanley [9] proved that $h_{i+1} \leq h_i^{<i>}$ (see section 3 for a definition of the $<i>$ -operator). By combining these two methods we show in Theorem 4.3 that if we define $g_i = h_i - h_{i-1}$, then $g_{i+1} \leq g_i^{<i>}$ for all $i < r/2$. All of these inequalities are immediate consequences of the existence of pairs (Θ, ω) such that Θ is a linear set of parameters for $k(\Delta)$ and ω is a g -element for $k(\Delta)/\langle \Theta \rangle$. Using a different approach, toric hyperkähler varieties, Hausel and Sturmfels proved the existence of g -elements for $k(\Delta)/\langle \Theta \rangle$ when the matroid is representable over the rationals [7]. A g -element is a one-form which acts like a Lefschetz class of a compact complex projective manifold except that it induces injections instead of bijections (Definition 4.1).

The broken circuit complex of a matroid is subcomplex of the independence complex and directly encodes the coefficients of the characteristic polynomial of the matroid. Every broken circuit complex is a cone, and if we remove the cone point we obtain a reduced broken circuit complex. Any independence complex is also a reduced broken circuit complex. Since the h -vector is unchanged by the removal of a cone point, the set of h -vectors of independence complexes is a (strict) subset of the set of h -vectors of broken circuit complexes. A natural question is whether or not Theorem 4.2 holds for broken circuit complexes. In Section 5 we

Partially supported by a VIGRE postdoc under NSF grant number 9983660 to Cornell University.

show that even if broken circuit complexes satisfy the corresponding combinatorial inequalities, there may be no set of linear parameters for the face ring such that there exist g -elements for the quotient ring.

Matroid terminology and notation closely follows [8]. The main exception to this is that we use $M - A$ for the deletion of a subset instead of $M \setminus A$. The ground set of the matroid M is always E .

2. COMPLEXES

Let Δ be a finite abstract simplicial complex with vertices $V = \{v_1, \dots, v_n\}$. The f -vector of Δ is the sequence $(f_0(\Delta), \dots, f_s(\Delta))$, where $f_i(\Delta)$ is the number of simplices of cardinality i and $s - 1$ is the dimension of Δ . The h -vector of Δ is the sequence $(h_0(\Delta), \dots, h_s(\Delta))$ defined by,

$$h_i(\Delta) = \sum_{k=0}^i (-1)^{i+k} f_k(\Delta) \binom{s-k}{i-k}.$$

Equivalently, if we let $f_\Delta(t) = f_0 t^s + f_1 t^{s-1} + \dots + f_{s-1} t + f_s$, then $h_\Delta(t) = h_0 t^s + h_1 t^{s-1} + \dots + h_{s-1} t + h_s$ satisfies $h_\Delta(1+t) = f_\Delta(t)$.

The *independence complex* of M is the simplicial complex whose vertices are the non-loop elements of E and whose simplices are the independent subsets of E . We let $\Delta(M)$ represent the independence complex of M .

In order to define the broken circuit complex for M , we first choose a linear order $\mathbf{n}$ on the elements of the matroid. Given such an order, a *broken circuit* is a circuit with its least element removed. The *broken circuit complex* is the simplicial complex whose simplices are the subsets of E which do not contain a broken circuit. We denote the broken circuit complex of M and $\mathbf{n}$ by $\Delta^{BC}(M)$, or $\Delta^{BC}(M, \mathbf{n})$. Different orderings may lead to different complexes, see [1, Example 7.4.4]. Conversely, distinct matroids can have the same broken circuit complex. For instance, let $E = \{e_1, e_2, e_3, e_4, e_5, e_6\}$, and let $\mathbf{n}$ be the obvious order. Let M_1 be the matroid on E whose bases are all triples except $\{e_1, e_2, e_3\}$ and $\{e_4, e_5, e_6\}$ and let M_2 be the matroid on E whose bases are all triples except $\{e_1, e_2, e_3\}$ and $\{e_1, e_5, e_6\}$. Then M_1 and M_2 are non-isomorphic matroids but their broken circuit complexes are identical. Both $h_{\Delta(M)}(t)$ and $h_{\Delta^{BC}(M)}(t)$ satisfy similar contraction-deletion formulas.

Proposition 2.1. [1], [3]

- (1) If e is a loop of M , then $h_{\Delta(M)}(t) = h_{\Delta(M-e)}(t)$, and $h_{\Delta^{BC}(M)}(t) = 1$.
- (2) If e is a coloop of M , then $h_{\Delta(M)}(t) = h_{\Delta(M-e)}(t)$, and $h_{\Delta^{BC}(M)}(t) = h_{\Delta^{BC}(M-e)}(t)$.
- (3) If e is neither a loop nor a coloop of M , then $h_{\Delta(M)}(t) = h_{\Delta(M-e)}(t) + h_{\Delta(M/e)}(t)$ and $h_{\Delta^{BC}(M)}(t) = h_{\Delta^{BC}(M-e)}(t) + h_{\Delta^{BC}(M/e)}(t)$.
- (4) If $M = M_1 \oplus M_2$, then $h_{\Delta(M)}(t) = h_{\Delta(M_1)}(t) \cdot h_{\Delta(M_2)}(t)$.
- (5) If S is a series class of M which is not a circuit, then $h_{\Delta(M)}(t) = h_{\Delta(M/S)}(t) + h_{\Delta(M-S)}(t)(1 + t + \dots + t^{|S|-1})$.

3. FACE RINGS

Let k be a field and let $R = k[x_1, \dots, x_n]$.

Definition 3.1. *The face ring of Δ is the graded k -algebra*

$$k[\Delta] = R/I_\Delta,$$

where I_Δ is the ideal generated by all monomials $x_{i_1} \cdots x_{i_l}$ such that $\{v_{i_1}, \dots, v_{i_l}\}$ is not a face of Δ .

Let $s - 1$ be the dimension of Δ . Let $\Theta = \{\theta_1, \dots, \theta_s\}$ be a set of one-forms in R . Write each $\theta_i = k_{i1}x_1 + \dots + k_{is}x_s$ and let $K = (k_{ij})$. To each simplex in Δ there is a corresponding set of column vectors in K . If for every simplex of Δ the corresponding set of column vectors is independent, then Θ is a *linear set of parameters* (l.s.o.p.) for $k(\Delta)$. If k is infinite, then it is always possible to choose Θ such that every set of s columns of K is independent.

Given a l.s.o.p. Θ for $k(\Delta)$ let $R(\Delta, \Theta) = k(\Delta)/\langle \Theta \rangle$. If Θ is unambiguous, then we just use $R(\Delta)$. Since Θ is homogeneous $R(\Delta)$ is a graded k -algebra.

Theorem 3.2. [9] *Let Θ be a l.s.o.p. for $\Delta(M)$ and let $R(\Delta(M))_i$ be the i^{th} graded component of $R(\Delta(M))$. Then $h_i(\Delta(M)) = \dim_k R(\Delta(M))_i$. Similarly, if Θ is a l.s.o.p. for $\Delta^{BC}(M)$, then $h_i(\Delta^{BC}(M)) = \dim_k R(\Delta^{BC}(M))_i$.*

Given any two integers $i, j > 0$ there is a unique way to write

$$j = \binom{a_i}{i} + \binom{a_{i-1}}{i-1} + \cdots + \binom{a_l}{l}, a_i > a_{i-1} > \cdots > a_l \geq l \geq 1.$$

Given this expansion define,

$$j^{<i>} = \binom{a_i+1}{i+1} + \binom{a_{i-1}+1}{i} + \cdots + \binom{a_l+1}{l+1}, a_i > a_{i-1} > \cdots > a_l \geq l \geq 1.$$

Theorem 3.3. [11, Theorem 2.2] *Let $Q = R/I$, where I is a homogeneous ideal. Let Q_i be the forms of degree i in Q and let $h_i = \dim_k Q_i$. Then $h_{i+1} \leq h_i^{<i>}$.*

Corollary 3.4. [9] *For any independence or broken circuit complex $h_{i+1} \leq h_i^{<i>}$.*

4. THE RING $R(\Delta(M))$

In order to study the properties of $h_i(\Delta(M))$ we will look for elements with properties slightly weaker than those provided by Lefschetz elements of the cohomology ring of a compact complex projective manifold.

Definition 4.1. *Let N be a (non-negatively) graded R -module whose dimension over k is finite. Let r be the last non-zero grade of N and let ω be a one-form in R . Then ω is a g -element for N if for all $i, 0 \leq i \leq r/2$, multiplication by ω^{r-2i} is an injection from N_i to N_{r-i} .*

If we replace injection with bijection in the above definition, then we obtain the strong Stanley property in [12].

Let M be a rank r matroid without coloops and k a field of characteristic zero. Let $n = |E|$. Write the elements of $k^{n \times (r+1)}$ in the form (Θ, ω) , where Θ consists of r elements in k^n and ω is also in k^n . Identify elements of k^n with the one-forms in R in the canonical way. Let U be the set of all pairs $(\Theta, \omega) \in k^{n \times (r+1)}$ such that Θ is a l.s.o.p. for $k(\Delta(M))$ and ω is a g -element for $R(\Delta(M), \Theta)$.

Theorem 4.2. *Let M, U and k be as above. Then, U is a non-empty Zariski open subset of $k^{n \times (r+1)}$.*

Proof. We first note that Θ is a l.s.o.p. for $k(\Delta)$ if and only if the determinants of the appropriate $r \times r$ minors of K are non-zero. Secondly, the multiplication maps ω^{r-2i} can be encoded as matrices which are polynomial in the coefficients of K and ω . Thus, U is the intersection of two Zariski open subsets of $k^{n \times (r+1)}$.

To show that U is not empty we proceed by induction on n . However, we use a slightly different (but equivalent) induction hypothesis. Let $C(j)$ be the circuit with j elements. Let P be a direct sum of circuits, so we can write $P = C(j_1) \oplus \cdots \oplus C(j_m)$. The rank of $M \oplus P$ is $r' = r + j_1 + \cdots + j_m - m$ and its cardinality is $n' = n + j_1 + \cdots + j_m$. The induction hypothesis is that given any such P , then $U = \{(\Theta, \omega) \in k^{n' \times (r'+1)} : \Theta \text{ is a l.s.o.p. for } k(\Delta(M \oplus P)) \text{ and } \omega \text{ is a } g\text{-element for } R(\Delta(M \oplus P), \Theta)\}$ is not empty. If M consists of a single loop, then $k(\Delta(M \oplus P)) \simeq k(\Delta(P))$. As a simplicial complex $\Delta(P)$ is $\partial(\Delta^{j_1-1}) * \cdots * \partial(\Delta^{j_m-1})$, where Δ^j is the j -simplex. Since this is the boundary of a convex rational polytope we can apply the Hard Lefschetz theorem as in [10] to see that U is not empty when $k = \mathbb{Q}$, and hence is not empty for any field of characteristic zero.

Suppose that M consists of a single coloop. Given P and Θ as in the above paragraph, $\Theta \cup \{x_{n'}\}$ is a l.s.o.p. for $k(\Delta(P \oplus M))$ and ω , which can be viewed as an element of $k[x_1, \dots, x_{n'}]$, is a g -element for $R(\Delta(P \oplus M), \Theta \cup \{x_{n'}\})$.

For the induction step, let S be a series class of M . Reordering M if necessary, we assume that $S = \{e_1, \dots, e_s\}$ consists of the first s elements of M . If S is a circuit, then $M = (M - S) \oplus C(s)$. Hence, $M \oplus P = (M - S) \oplus (C(s) \oplus P)$ and the induction hypothesis applies to $M - S$. So assume that S is independent. Let $x^S = x_1 \cdots x_s$. For Θ a l.s.o.p. for $k(\Delta(M \oplus P))$ consider the following short exact sequence.

$$(1) \quad 0 \rightarrow \frac{\langle x^S \rangle R}{\langle x^S \rangle \cap (\Theta + I_{\Delta(M \oplus P)})} \rightarrow R(\Delta(M \oplus P), \Theta) \rightarrow \frac{R(\Delta(M \oplus P), \Theta)}{\langle x^S \rangle} \rightarrow 0.$$

Since S is a series class, a subset of $M - S$ is independent if and only if its union with any proper subset of S is independent. Hence, the right-hand side is just $R(\Delta((M - S) \oplus (C(s) \oplus P), \Theta))$. Therefore, we can apply the induction hypothesis to $M - S$ to obtain a non-empty Zariski open subset U' of $k^{n \times (r+1)}$ consisting of pairs (Θ', ω') such that ω' is a g -element for $R(\Delta((M - S) \oplus C(s) \oplus P), \Theta')$.

In order to analyze the left-hand side of (1) choose generators $\{\theta_1, \dots, \theta_s, \dots, \theta_{r'}\}$ for $\langle \Theta \rangle$ so that in the corresponding matrix K , $k_{ij} = \delta_{ij}$ for $1 \leq i \leq s$. Now define an R -module structure on $R' = k[x_{s+1}, \dots, x_{n'}]$ by defining $(x_i) \cdot f = (x_i - \theta_i) \cdot f$ for $1 \leq i \leq s$ and $f \in R'$. Let $\phi : R' \rightarrow (\langle x^S \rangle R) / (\Theta + I_{\Delta(M \oplus P)})$ be multiplication by x^S . Since S is independent, every polynomial in $(\langle x^S \rangle R) / (\Theta + I_{\Delta(M \oplus P)})$ is equivalent to a polynomial in $\langle x^S \rangle R'$. So, ϕ is surjective. The kernel of ϕ contains $\Theta' = \{\theta \in \Theta : \theta = k_{s+1}x_{s+1} + \cdots + k_{n'}x_{n'}\}$. In addition, $\ker \phi$ contains all monomials in $I_{\Delta((M/S) \oplus P)}$. Since Θ' is a l.s.o.p. for $k(\Delta(M/S))$, we see that ϕ is a degree s graded surjective R -module homomorphism from $R' / (I_{\Delta((M/S) \oplus P)} + \Theta')$ to the left-hand side of (1). Proposition 2.1 and $h_{\Delta(C(s))}(t) = 1 + t + \cdots + t^{s-1}$ show that the k -dimension of $R' / (\Delta(M/S), \Theta')$ and the l.h.s. of (1) are the same. Hence ϕ is an isomorphism. Therefore, by the induction hypothesis applied to M/S , there is a non-empty Zariski open subset U'' of $k^{n \times (r+1)}$ consisting of pairs (Θ'', ω'') such that the multiplication map

$$\omega''^{(r'-2i-s)} : \left(\frac{\langle x^S \rangle R}{\langle x^S \rangle \cap (\Theta'' + I_{\Delta(M \oplus P)})} \right)_{i+s} \rightarrow \left(\frac{\langle x^S \rangle R}{\langle x^S \rangle \cap (\Theta'' + I_{\Delta(M \oplus P)})} \right)_{r'-i}$$

is an injection for $1 \leq i \leq (r' - s)/2$. Now, $U' \cap U'' \subseteq U$. Since the intersection of two non-empty Zariski open subsets of $k^{n \times (r+1)}$ is not empty, U is also not empty. $\square$

Theorem 4.3. *Let M be a rank r matroid without coloops. Let $h_i = h_i(\Delta(M))$. Then,*

- (1) $h_0 \leq \dots \leq h_{\lfloor r/2 \rfloor}$.
- (2) $h_i \leq h_{r-i}$ for all $i \leq r/2$.
- (3) Let $g_i = h_i - h_{i-1}$. Then, for all $i < r/2$, $g_{i+1} \leq g_i^{<i>}$.

Proof. The first two inequalities follow from the injectivity properties of any g -element ω for $R(\Delta(M), \Theta)$. Since $g_i = (R(\Delta(M), \Theta) / \langle \omega \rangle)_i$ when $i < r/2$, the last inequality follows from Theorem 3.3. $\square$

The first two inequalities were obtained by Chari using a PS-ear decomposition of $\Delta(M)$. See [5] for details on PS-ear decompositions. Hausel and Sturmfels used toric hyperkähler varieties to prove the last inequality for matroids representable over the rationals [7]. The proof of Theorem 4.2 is essentially an algebraic version of a PS-ear decomposition [6, Theorem 2]. Indeed, the proof works without change for any simplicial complex with a PS-ear decomposition.

5. THE RING $R(\Delta^{BC}(M))$

As shown in [2] the cone on any independence complex is a broken circuit complex (for some other matroid). Since the h -vector of the cone of a simplicial complex is the same as the h -vector of the original complex, the h -vectors of independence complexes form a (strict) subset of the h -vectors of broken-circuit complexes. It is natural to ask whether or not Theorem 4.2 holds for $\Delta^{BC}(M)$. The last non-zero element of the h -vector of $\Delta^{BC}(M)$ is $r-m$, where m is the number of components of M . It is not difficult to modify the proof of Theorem 4.2 to produce injections from $R(\Delta^{BC}(M))_0$ to $R(\Delta^{BC}(M))_{r-m}$ and from $R(\Delta^{BC}(M))_1$ to $R(\Delta^{BC}(M))_{r-m-1}$. Since the first possible problem is in degree 2, the smallest possible rank of M for which Theorem 4.2 does not hold for $\Delta^{BC}(M)$ is six.

Let $G(s)$ be the graph obtained by subdividing each edge of the graph consisting of s parallel edges into two edges. Let $M(s)$ be the cycle matroid of $G(s)$. The rank of $M(s)$ is $s+1$ and $M(s)$ has $2s$ elements.

Proposition 5.1. *Let Θ be a l.s.o.p. for $M(s)$, $\mathbf{n}$ a linear order of the elements of $M(s)$ and ω a linear form in $k[x_1, \dots, x_{2s}]$. Then, multiplication by ω has a non-trivial kernel in $R(\Delta^{BC}(M))_2$.*

Proof. Let E_l consist of the greatest l elements of $M(s)$ with respect to $\mathbf{n}$. Let $\{e_i, e_j\}$ be the first pair of edges to appear in E_l as l goes from 1 to $s+1$ such that they come from the subdivision of one of the parallel edges used to construct $G(s)$. Consider the ideal $\langle x_i x_j \rangle \subseteq R(\Delta^{BC}(M, \mathbf{n}))$. Using the same reasoning as in the proof of Theorem 4.2, the choice of $\{e_i, e_j\}$ implies that $\langle x_i x_j \rangle$ is isomorphic as an R -module to $R'(\Delta^{BC}(\Delta(M(s)/\{e_i, e_j\}, \mathbf{n}'), \Theta'))$, where R' and Θ' are defined as in the proof of Theorem 4.2, and $\mathbf{n}'$ is the order on $M(s)/\{e_i, e_j\}$ induced from

n. Now, $M(s)/\{e_i, e_j\}$ is the cycle matroid of the $G(s)$ with the two edges $\{e_i, e_j\}$ contracted. For any such pair and any linear order $\Delta^{BC}(M(s)/\{e_i, e_j\})$ is an $s - 2$ dimensional simplex. Hence $\langle x_i x_j \rangle \simeq k$ and will vanish under any multiplication map. $\square$

Repeated application of Proposition 2.1 shows that $h_i(\Delta^{BC}(M(s))) = \binom{s}{i}$ when $i \neq 1$ and $h_1(\Delta^{BC}(M(s))) = s - 1$. When $s \geq 5$, the h -vector of the broken circuit complex of $M(s)$ satisfies the combinatorial conditions of Theorem 4.3 but there is no l.s.o.p. for the face ring such that the quotient ring has g -elements. As far as we know, whether or not broken circuit complexes satisfy the combinatorial inequalities of Theorem 4.3 remains an open question.

Acknowledgement: Louis Billera suggested the problem of determining whether or not independence complexes satisfied $g_{i+1} \leq g_i^{<i>}$.

REFERENCES

- [1] A. Björner. The homology and shellability of matroids and geometric lattices. In N. L. White, editor, *Matroid Applications*, pages 226 – 283. Cambridge University Press, 1992.
- [2] T. Brylawski. The broken-circuit complex. *Trans. Amer. Math. Soc.*, 234:417–33, 1977.
- [3] T. Brylawski and J. G. Oxley. The Tutte polynomial and its applications. In N. L. White, editor, *Matroid Applications*, pages 123 – 225. Cambridge University Press, 1992.
- [4] M. Chari and C. Colbourn. Reliability polynomials: A survey. *Journal of Combinatorics, Information & System Sciences*, 22:177–193, 1997.
- [5] M.K. Chari. Matroid inequalities. *Discrete Math.*, 147:283–286, 1995.
- [6] M.K. Chari. Two decompositions in topological combinatorics with applications to matroid complexes. *Trans. Amer. Math. Soc.*, 349:3925–3943, 1997.
- [7] T. Hausel and B. Sturmfels. Toric hyperkähler varieties. arXiv: math.AG/0203096, 2002.
- [8] J. G. Oxley. *Matroid Theory*. Oxford University Press, Oxford, 1992.
- [9] R.P. Stanley. Cohen-Macaulay complexes. In M. Aigner, editor, *Higher combinatorics*, pages 51–62, Dordrecht and Boston, 1977. Reidel.
- [10] R.P. Stanley. The number of faces of a simplicial convex polytope. *Advances in Math.*, 35:236–238, 1980.
- [11] R.P. Stanley. *Combinatorics and commutative algebra*. Progress in Mathematics, 41. Birkhäuser Boston, Inc., 1996.
- [12] J. Watanabe. The Dilworth number of Artinian rings and finite posets with rank function. In *Commutative algebra and combinatorics*, Adv. Stud. Pure Math. 11, pages 303–312, 1985.

MALOTT HALL, CORNELL UNIVERSITY, ITHACA, NY14853
E-mail address: ebs@math.cornell.edu